

# DATASHEET

- TC/mV/VC/RB universal input in one product
- Two Independent Alarm/Trip Relay Outputs
- 2A / 30Vdc contact rating
- 0-20mA / 0-±10V / 0-±10mA universal output
- Built-in "rate of change" alarm
- 24Vdc powered
- Three port isolation to 1500Vac
- Software configurable
- Output overload detection

# Features

- DIN Rail or surface mountable
- Narrow 45mm module width
- 20 30V dc powered.
- 1500Vac Isolation Input/Output/Power Supply
- Output overload Indicator

## OVERVIEW

The OMNITERM TTT Universal Input Dual Trip Module with additional Transmitter Output is designed for the widest range of signal conditioning and alarm/trip applications in a single off-the-shelf product, using advanced state-of-the-art digital measurement techniques, combined with extremely user friendly software configurability.

The input will accommodate most thermocouple and resistance bulb types, as well as voltages and currents from 1mV minimum to 10Vdc maximum input span. (Extended ranges are available – see Order Codes)

This module has both Analogue transmitter output as well as two fully configurable alarm/trip relay contacts with "rate of change" alarms built in.

The analogue output can be configured for unipolar or bipolar outputs of current or voltage from  $\pm 1$ mA to  $\pm 10$ mA; 0-20mA; or  $\pm 1$ V to  $\pm 10$ V.

Full isolation (input/output/power supply) to 1500Vac ensures trouble-free accurate measurement.

This product provides extremely low life-cycle costs by reducing spares stock-holding requirements, and reducing specialist technical expertise required for field



- User friendly configuration software
- Wide operating temperature range
- Linearised for all standard input types
- Special function options included as standard
- Designed to meet IEC 61508 SIL1 criteria.

support, module replacement and field configuration. This new holistic approach to instrumentation asset management ensures reliable performance and minimal down-time.

Using advanced Sigma-Delta A/D technology combined with sophisticated digital filtering techniques, the TTT offers 16-bit measurement resolution with increased dynamic range, tailored for noisy plant environments.

## CONFIGURATION MANAGEMENT

The powerful but intuitive configuration software ensures the maximum instrument flexibility with reliable configuration management to ensure all instruments on the plant are always correctly configured to the design requirements specification.

### HIGH RELIABILITY

This product has been designed with high reliability applications in mind. The output stage has built in overload indication to detect overloaded output circuits – whether from a wire break or just excess resistance in the line.


This product has been designed to meet the criteria of IEC61508 for SIL1 applications.








# **Electrical Connections**






### OUTPUT RANGE SELECTION AND CONNECTIONS







# **Mechanical Details**



# Specifications

#### Input

#### **Measurement Types and Ranges**

Unless otherwise stated, all specifications refer to Model C2467B-0

#### THERMOCOUPLES (TC Input Ranges covered)

	- /
Type B (Pt30Rh-Pt6Rh)	400 – 1820 °C (400 °C min. span*)
Type E (NiCr-CuNi)	-150 – 1000 °C (80 °C min. span*)
Type J (Fe-CuNi)	-210 – 1200 °C (100 °C min. span*)
Type K (NiCr-NiAl)	-270 – 1372 °C (100 °C min. span*)
Type N (NiCrSi-NiSiMg)	0 – 1300 °C (175 °C min. span*)
Type R (Pt13Rh-Pt)	-50 – 1767 °C (500 °C min. span*)
Type S (Pt10Rh-Pt)	-50 – 1767 °C (500 °C min. span*)
Type T (Cu-CuNi)	-270 – 400 °C (100 °C min. span*)
Type W()	1000 – 2500 °C(1000 °C min.span*)
Type W5 (Re/W26-Re)	0 – 2320 °C (300 °C min. span*)
Type W3 (Re/W25-Re)	0 – 2500 °C (300 °C min. span*)
*Minimum Span	May be lower but with reduced accuracy overall
Cold Junction Compensation	Internal
CJC Accuracy	< 0.5 °C over 0 – +40 °C <1 °C over –10 – +60 °C
TC Burnout Detection	Settable upscale or downscale
RESISTANCE THERMOMETER	RS (RB Input Ranges)
Model C2467B-0	2 or 3 wire connection
Model C2467B-1	True 4-wire connection

Model C2467B-0	2 or 3 wire connection
Model C2467B-1	True 4-wire connection
Measuring Current	200μA nominal 20μA for Model C2467B-3 1000μA for Model C2467B-4
Lead Resistance	≤ 100 ohms per lead
Pt100 (IEC60751/DIN43760)	-200 – 850 °C (50 °C min. span)
Ni100 (DIN43760)	-60 – 250 °C (50 °C min. span)
Ni120	-80 – 320°C (50°C min. span)
Pt500 (model C2467B-3)	-200 – 630°C (50°C min. span)

Pt1000 (model C2467B-3)       -200 – 630°C (50 °C min. span)         Cu10 (model C2467B-4)       -100 – 260°C (50 °C min. span)         Wodel C2467B-0       -1 – +10V (min. span 0.1V)         Model C2467B-2       -1 – +60V (min. span 5V)         Input Impedance       > 1MΩ         MILLIVOLTS (mV Input Ranges)       Millivolts         Millivolts       -10 – 100mV (min. span 1mV)         Input Impedance       > 10MΩ         CURRENT (I Input Range)       > 10MΩ         Current       0 – 25mA (0.2 mA min. span)         Current Input Burden       <5 ohms         Supply for two – wire transmitters       24V nom.         CUSTOM (Any Input Range)       ZuV nom.         Custom Sensor Ranging       Many additional ranges are User Configurable using the Configuration Software         Analogue Output       >10 – +10V max (min span 1V)         Load Resistance       >1kohm         VULTAGE       >1kohm         Output Voltage Max. Range       -10 – +10V max (min span 1mA)         Load Resistance       ≤1kohm         BIPOLAR CURRENT       Output Current Max. Range         Output Current Max. Range       -10 – +10 mA (min span 1mA)         Load Resistance       ≤1kohm		
VOLTS (V Input Ranges)Model C2467B-0 $-1 - +10V$ (min. span 0.1V)Model C2467B-2 $-1 - +60V$ (min. span 5V)Input Impedance> 1MQMILLIVOLTS (mV Input Ranges)Millivolts $-10 - 100mV$ (min. span 1mV)Input Impedance> 10MQCURRENT (I Input Range)Current $0 - 25mA$ (0.2 mA min. span)Current Input Burden<5 ohms	Pt1000 (model C2467B-3)	-200 – 630°C (50 °C min. span)
Model C2467B-0 $-1 - +10V$ (min. span 0.1V)Model C2467B-2 $-1 - +60V$ (min. span 5V)Input Impedance> 1MQMILLIVOLTS (mV Input Ranges)Millivolts $-10 - 100mV$ (min. span 1mV)Input Impedance> $20MQ$ CURRENT (I Input Range) $0 - 25mA (0.2 mA min. span)$ Current $0 - 25mA (0.2 mA min. span)$ Current Input Burden $<5 \text{ ohms}$ Supply for two – wire transmitters $24V$ nom.CUSTOM (Any Input Range)Many additional ranges are User Configurable using the Configuration SoftwareAnalogue OutputMany additional ranges are User Configurable using the Configuration SoftwareVoLTAGE $-10 - +10V$ max (min span 1V)Load Resistance $\geq 1kohm$ UNIPOLAR CURRENT $0 - 20 mA$ (min span 1mA)Load Resistance $<10 - 20 mA$ (min span 1mA)Load Resistance $<10 - 20 mA$ (min span 1mA)Load Resistance $<1kohm$	Cu10 (model C2467B-4)	-100 – 260°C (50 °C min. span)
Model C2467B-2 $-1 - +60V$ (min. span 5V)Input Impedance> 1MQMILLIVOLTS (mV Input Ranges)Millivolts $-10 - 100mV$ (min. span 1mV)Input Impedance> 10MQCURRENT (I Input Range)> 10MQCurrent $0 - 25mA$ ( $0.2 mA$ min. span)Current Input Burden<5 ohms	VOLTS (V Input Ranges)	
Input Impedance       > 1MΩ         MILLIVOLTS (mV Input Ranges)         Millivolts       -10 – 100mV (min. span 1mV)         Input Impedance       >10MΩ         CURRENT (I Input Range)          Current       0 – 25mA (0.2 mA min. span)         Current Input Burden       <5 ohms	Model C2467B-0	-1 – +10V (min. span 0.1V)
MILLIVOLTS (mV Input Ranges)         Millivolts       -10 – 100mV (min. span 1mV)         Input Impedance       >10MΩ         CURRENT (I Input Range)          Current       0 – 25mA (0.2 mA min. span)         Current Input Burden       <5 ohms	Model C2467B-2	-1 – +60V (min. span 5V)
Millivolts-10 - 100mV (min. span 1mV)Input Impedance>10MΩCURRENT (I Input Range)Current0 - 25mA (0.2 mA min. span)Current Input Burden<5 ohms	Input Impedance	> 1MΩ
Input Impedance       >10MΩ         CURRENT (I Input Range)       0 - 25mA (0.2 mA min. span)         Current Input Burden       <5 ohms	MILLIVOLTS (mV Input Ranges)	
CURRENT (I Input Range)Current0 – 25mA (0.2 mA min. span)Current Input Burden<5 ohms	Millivolts	-10 – 100mV (min. span 1mV)
Current $0 - 25mA (0.2 mA min. span)$ Current Input Burden<5 ohms	Input Impedance	>10MΩ
Current Input Burden<5 ohms	CURRENT (I Input Range)	
Supply for two – wire transmitters24V nom.CUSTOM (Any Input Range)Custom Sensor RangingMany additional ranges are User Configurable using the Configuration SoftwareAnalogue OutputOutput Types and RangesVOLTAGEOutput Voltage Max. Range Load Resistance-10 - +10V max (min span 1V) ≥1kohmUNIPOLAR CURRENTOutput Current Max. Range Load Resistance0 - 20 mA (min span 1mA) ≤1kohmBIPOLAR CURRENTOutput Current Max. Range-10 - +10 mA (min span 1mA)Load ResistanceSinter SoftwareOutput Current Max. Range0 - 20 mA (min span 1mA)Load ResistanceSinter SoftwareOutput Current Max. Range0 - 20 mA (min span 1mA)Load ResistanceSinter SoftwareSinter SoftwareSinter SoftwareSoftwa	Current	0 – 25mA (0.2 mA min. span)
transmitters CUSTOM (Any Input Range) Custom Sensor Ranging Many additional ranges are User Configurable using the Configuration Software Analogue Output Output Types and Ranges VOLTAGE Output Voltage Max. Range -10 - +10V max (min span 1V) Load Resistance 21kohm UNIPOLAR CURRENT Output Current Max. Range 0 - 20 mA (min span 1mA) Load Resistance SIPOLAR CURRENT Output Current Max. Range -10 - +10 mA (min span 1mA)	Current Input Burden	<5 ohms
Custom Sensor RangingMany additional ranges are User Configurable using the Configuration SoftwareAnalogue OutputImage: Configurable using the Configuration SoftwareOutput Types and RangesImage: Configurable using the Configuration SoftwareVOLTAGEImage: Configurable using the Configuration SoftwareOutput Voltage Max. Range-10 - +10V max (min span 1V) ≥1kohmImage: Configurable using the Configuration SoftwareImage: Configurable using the Configuration SoftwareOutput Voltage Max. Range-10 - +10V max (min span 1V) ≥1kohmImage: Configurable using the Configuration ≥1kohmImage: Configurable using the Configuration ≥1kohmOutput Current Max. Range0 - 20 mA (min span 1mA) ≤1kohmBIPOLAR CURRENTImage: Configurable using the Configuration ≤1kohmOutput Current Max. Range-10 - +10 mA (min span 1mA)		24V nom.
Configurable using the Configuration SoftwareAnalogue OutputOutput Types and RangesVOLTAGEOutput Voltage Max. Range-10 - +10V max (min span 1V)Load Resistance≥1kohmUNIPOLAR CURRENTOutput Current Max. Range0 - 20 mA (min span 1mA)Load Resistance≤1kohmBIPOLAR CURRENTOutput Current Max. Range0 - 20 mA (min span 1mA)Load Resistance≤1kohm	CUSTOM (Any Input Range)	
Output Types and Ranges         VOLTAGE         Output Voltage Max. Range       -10 - +10V max (min span 1V)         Load Resistance       ≥1kohm         UNIPOLAR CURRENT       0 - 20 mA (min span 1mA)         Load Resistance       ≤1kohm         BIPOLAR CURRENT       0 - 20 mA (min span 1mA)         Output Current Max. Range       0 - 20 mA (min span 1mA)         Doutput Current Max. Range       -10 - +10 mA (min span 1mA)	Custom Sensor Ranging	Configurable using the Configuration
VOLTAGEOutput Voltage Max. Range $-10 - +10V \max (\min span 1V)$ Load Resistance $\geq 1kohm$ UNIPOLAR CURRENTOutput Current Max. Range $0 - 20 mA (\min span 1mA)$ Load Resistance $\leq 1kohm$ BIPOLAR CURRENTOutput Current Max. Range $-10 - +10 mA (\min span 1mA)$	Analogue Output	
Output Voltage Max. Range $-10 - +10V \max (\min \text{ span } 1V)$ Load Resistance $\geq 1 \text{kohm}$ UNIPOLAR CURRENT $0 - 20 \text{ mA (min span } 1\text{mA})$ Load Resistance $\leq 1 \text{kohm}$ BIPOLAR CURRENT $0 - 20 \text{ mA (min span } 1\text{mA})$ Output Current Max. Range $0 - 20 \text{ mA (min span } 1\text{mA})$ Load Resistance $\leq 1 \text{kohm}$ BIPOLAR CURRENT $-10 - +10 \text{ mA (min span } 1\text{mA})$	Output Types and Ranges	
Load Resistance       ≥1kohm         UNIPOLAR CURRENT         Output Current Max. Range       0 – 20 mA (min span 1mA)         Load Resistance       ≤1kohm         BIPOLAR CURRENT       Output Current Max. Range         Output Current Max. Range       -10 – +10 mA (min span 1mA)	VOLTAGE	
UNIPOLAR CURRENT       Output Current Max. Range     0 - 20 mA (min span 1mA)       Load Resistance     ≤1kohm       BIPOLAR CURRENT     Output Current Max. Range       Output Current Max. Range     -10 - +10 mA (min span 1mA)	Output Voltage Max. Range	-10 – +10V max (min span 1V)
Output Current Max. Range       0 – 20 mA (min span 1mA)         Load Resistance       ≤1kohm         BIPOLAR CURRENT         Output Current Max. Range       -10 – +10 mA (min span 1mA)	Load Resistance	≥1kohm
Load Resistance       ≤1kohm         BIPOLAR CURRENT         Output Current Max. Range       -10 - +10 mA (min span 1mA)	UNIPOLAR CURRENT	
BIPOLAR CURRENT       Output Current Max. Range       -10 - +10 mA (min span 1mA)	Output Current Max. Range	0 – 20 mA (min span 1mA)
Output Current Max. Range -10 – +10 mA (min span 1mA)	Load Resistance	≤1kohm
	BIPOLAR CURRENT	
Load Resistance ≤1kohm	Output Current Max. Range	-10 – +10 mA (min span 1mA)
	Load Resistance	≤1kohm







PULSE	
Pulse Rates available	Low Range: 100-1000 pulses/hr (pulse output width 500ms) High Range: 1000-10000 pulses/hr (pulse output width 60ms)
Transistor switched output	20V min; 30V max. designed to operate with a 24V relay or equivalent.
Load Resistance	≥ 860 ohms
Accuracy	
Initial Error	<0.1%
<b>N N N</b>	0.404

Non-linearity	<0.1%
Temperature Drift	< 150ppm/°C
TC linearisation error (types B, E, J, K, N, T)	<0.25 °C or 0.1% of reading (whichever is greater) <0.5 °C below –100 °C
TC linearisation error (types R, S, W3, W5)	<2.0 °C
TC linearisation error (type W)	<2.5 °C

### **Selectable Computation Functions**

1. Signal Inversion

2. Square Root

3. Integration output pulses instead of analogue output

### Alarm/Trip Relay contacts

Number of relays	2 (One per alarm/trip point)
High or Low setting	Configurable to be energised above or below the setpoint.
"Rate of Change" Alarms	Fast (per second) Slow (per minute)
Source	From AL1 & AL2 Alarm setpoints
Terminal/wire size	0.14 – 2.5mm <sup>2</sup> stranded
Contact type	SPST (Form A) per relay
Contact Rating	2A 30VDC ; 0.5A 250VAC
Contact Isolation Test/Operating Voltage	1500Vac Isolation 250Vac operating.
Response Time	<20ms for input change 10-90%

### Alarm/Trip Setpoints

Number of setpoints	2 (One for each Relay)
Settable Range	Full span of the instrument
Repeatability	<0.1%
Deadband	Settable 0.1 to 100%

# Indicator LED's

OK LED (Green)	
ON Steady	Unit is powered and operating correctly
Single Flash every second	Input Fault.
Double Flash every second	Analogue Output Fault
Triple Flash every second	Configuration Fault.
AL1 and AL2 Alarm/Trip indica	ator LED's (Red)
AL1 ON Steady	ON when relay RL1 is energised.
AL2 ON Steady	ON when relay RL2 is energised.

24 Volts -15% / +25% (20-30Vdc)

# Power Supply

Supply Voltage

0

SGS

Copyright Omniflex • Subject to change without notice Datasheet DSC2467BR06 sheet 4 of 4

Current Consumption	80mA max. plus output current	
Configuration		
Input Type	Field selectable via 4 way DIP switch (Accessed from top of module)	
Output Type	Field selectable via 4 way DIP switch (Accessed from bottom of module)	
Range	Field selectable via programming port on front of unit with the aid of a PC and configuration software package.	
<b>Environmental Cond</b>	litions	
Operating Temperature	-10°C – 60 °C (+14°F – 140°F)	
Storage Temperature	-25°C – 85 °C (-13°F – 185°F)	
Reliability Data		
MTBF	35.7 years	
PFD (TI = 2 years)	5.41 x 10 <sup>-3</sup>	
SFF	81%	
Compliance with Standards		
Safety	EN 60950	
Emissions	EN 55011 Group I, Class A	
Immunity – ESD	IEC 61000-4-2	
Immunity – RF Fields	IEC 61000-4-3	
Immunity – Fast	IEC 61000-4-4	
Transients	2 kV – DC power port 1 kV – input/output lines	
Insulation	Basic Insulation between isolated circuits	
	per IEC950	
Insulation Test Voltage	Input/Output/Supply 100% tested to 1500Vac	
Mechanical		
Dimensions(W x H x D)	45 x 75 x 100mm	
Mounting	Snaps on to DIN rail EN50022-35 Or screws to vertical surface	
Housing	Shock resistant ABS	
Flammability	UL94-HB (Housing) ; UL94-V0 (Terminals)	
Terminal/wire size	0.14 – 2.5mm <sup>2</sup> stranded	
Weight		
Unpacked	170gm approx.	
Packed	210gm approx.	
Ordering Information		
ORDER CODE	DESCRIPTION	
C2467B-0	Omniterm TTT Dual Trip & Transmitter (standard model).	
C2467B-1	Omniterm TTT with 4 wire RTD input	
C2467B -2	Omniterm TTT with Hi Voltage Input	
C2467B -3	Omniterm TTT with low current excitation for Pt1000 etc.	
C2467B -4	Omniterm TTT with high current excitation for Cu10 etc.	
ACCESSORIES		
C1168	Omniflex Miniature Jack Programming Cable.	



